

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES


Defective images within this document are accurate representations of the original documents submitted by the applicant.


Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**





I hereby certify that this correspondence
is being deposited with the United States
Postal Service with sufficient postage as
first class mail in an envelope addressed to:

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

Richard J. Coldren
Attorney for Applicant

Date: 11 March 2004

Application No. : 10/689,366
Applicant : Mark Beaumont
Filed : 20 October 2003
Title : METHOD FOR MANIPULATING DATA IN A GROUP OF
PROCESSING ELEMENTS TO PERFORM A REFLECTION OF
THE DATA

TC/A.U. : Not yet assigned
Examiner : Not yet assigned

Atty. Docket No. : DB001071-000
Customer No. : 24122

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

TRANSMITTAL LETTER

Dear Sir:

Enclosed for filing in the above-captioned application, please find the following:

- Submission of Foreign Priority Document UK Patent Application No. 0309195.6 as required Under 35 U.S.C. §119 and 37 C.F.R. §1.55.

Also enclosed is a return postcard. Please date stamp the postcard and return it to us to acknowledge receipt of this patent application.

The Commissioner is hereby authorized to charge any underpayment or credit any overpayment to our Deposit Account No. 20-0888. A duplicate copy of this Transmittal letter is enclosed.


Respectfully submitted,

Richard J. Coldren

Richard J. Coldren
Reg. No. 44,084
THORP REED & ARMSTRONG, LLP
One Oxford Centre, 14th Floor
301 Grant Street
Pittsburgh, PA 15219-1425
(412) 394-2442

Attorney for Applicant

Dated: 11 March 2004





I hereby certify that this correspondence
is being deposited with the United States
Postal Service with sufficient postage as
first class mail in an envelope addressed to:

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

Richard J. Coldren
Attorney for Applicant

Date: 11 March 2004

Application No. : 10/689,366
Applicant : Mark Beaumont
Filed : 20 October 2003
Title : METHOD FOR MANIPULATING DATA IN A GROUP OF
PROCESSING ELEMENTS TO PERFORM A REFLECTION OF
THE DATA

TC/A.U. : Not yet assigned
Examiner : Not yet assigned

Atty. Docket No. : DB001071-000
Customer No. : 24122

Commissioner for Patents
P.O. Box 1450
Alexandria, VA 22313-1450

TRANSMITTAL LETTER

Dear Sir:

Enclosed for filing in the above-captioned application, please find the following:

- Submission of Foreign Priority Document UK Patent Application No. 0309195.6 as required Under 35 U.S.C. §119 and 37 C.F.R. §1.55.

Also enclosed is a return postcard. Please date stamp the postcard and return it to us to acknowledge receipt of this patent application.

The Commissioner is hereby authorized to charge any underpayment or credit any overpayment to our Deposit Account No. 20-0888. A duplicate copy of this Transmittal letter is enclosed.


Respectfully submitted,

Richard J. Coldren

Richard J. Coldren
Reg. No. 44,084
THORP REED & ARMSTRONG, LLP
One Oxford Centre, 14th Floor
301 Grant Street
Pittsburgh, PA 15219-1425
(412) 394-2442

Attorney for Applicant

Dated: 11 March 2004





INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation and Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein together with the Statement of inventorship and of right to grant of a Patent (Form 7/77), which was subsequently filed.


In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

Dated 27 February 2004



1/77
24APR03 EBO2074-8 D00589
P01/7700 0.00-0309195.6

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road
Newport
South Wales
NP10 8QQ

1. Your reference

P17553GB-JCC/lp

2. Patent application number

(The Patent Office will fill in this part)

0309195.6

23 APR 2003

3. Full name, address and postcode of the or of each applicant (underline all surnames)

Micron Europe Limited,
Micron House,
Wellington Business Park,
Dukes Ride, Crowthorne,
Berkshire RG45 6LS

Patents ADP number (if you know it)

8291817002

If the applicant is a corporate body, give the country/state of its incorporation

UK (all recd) 13.6.03

4. Title of the invention

METHOD FOR MANIPULATING DATA IN A GROUP OF PROCESSING
ELEMENTS TO PERFORM A REFLECTION OF THE DATA

5. Name of your agent (if you have one)

Forrester Ketley & Co.

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

Forrester House
52 Bounds Green Road
London
N11 2EY

Patents ADP number (if you know it)

133001

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country	Priority application number (if you know it)	Date of filing (day / month / year)
GB	0221562.2	17/09/2002
GB	0221563.0	17/09/2002

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing (day / month / year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if:

YES

- a) any applicant named in part 3 is not an inventor, or
 - b) there is an inventor who is not named as an applicant, or
 - c) any named applicant is a corporate body.
- See note (d))

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description	15
Claim(s)	3
Abstract	1
Drawing(s)	8

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77)

Request for preliminary examination and search (Patents Form 9/77)

1

Request for substantive examination (Patents Form 10/77)

Any other documents (please specify)

11.

I/We request the grant of a patent on the basis of this application.

Signature
Forrester Ketley & Co.

Date
14 April 2003

12. Name and daytime telephone number of person to contact in the United Kingdom

(020) 8889 6622

J.C. Carstairs

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 08459 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.


Patents Form 7/77

Patents Act 1977
(Rule 15)



7/77

Statement of inventorship and of
right to grant of a patent



The Patent Office

Cardiff Road
Newport
South Wales
NP10 8QQ

1. Your reference P17553GB-JCC/lp
2. Patent application number (if you know it) 0309195.6
3. Full name of the or of each applicant Micro Europe Limited 06MAY03 0130950-1 000389 P07/7700 0.00-0309195.6
4. Title of the invention METHOD FOR MANIPULATING DATA IN A GROUP OF PROCESSING ELEMENTS TO PERFORM A REFLECTION OF THE DATA
5. State how the applicant(s) derived the right from the inventor(s) to be granted a patent As employers of the inventor
6. How many, if any, additional Patents Forms 7/77 are attached to this form? (see note (c))
7. I/We believe that the person(s) named over the page (and on any extra copies of this form) is/are the inventor(s) of the invention which the above patent application relates to.
Signature *Forrester Ketley & Co.* Date 2 May 2003
Forrester Ketley & Co.
8. Name and daytime telephone number of person to contact in the United Kingdom (020) 8889 6622 CARSTAIRS, J.C.

Notes

- a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 08459 500505.
- b) Write your answers in capital letters using black ink or you may type them.
- c) If there are more than three inventors, please write the names and addresses of the other inventors on the back of another Patents Form 7/77 and attach it to this form.
- d) When an application does not declare any priority, or declares priority from an earlier UK application, you must provide enough copies of this form so that the Patent Office can send one to each inventor who is not an applicant.
- e) Once you have filled in the form you must remember to sign and date it.

Patents Form 7/77

Enter the full names, addresses and postcodes of the inventors in the boxes and underline the surnames

Mark BEAUMONT,
30 Lorne Street,
Reading,
RG1 7YN
Berkshire,
United Kingdom

8623191001

Patents ADP number *(if you know it):*

Patents ADP number *(if you know it):*

Patents ADP number *(if you know it):*

Reminder

Have you signed the form?

Patents Form 7/77

DUPLICATE

METHOD FOR MANIPULATING DATA IN A GROUP OF PROCESSING ELEMENTS TO PERFORM A REFLECTION OF THE DATA

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] The present application is related to the following applications: Method for Manipulating Data in a Group of Processing Elements (docket no. DB001072-000); Method for Manipulating Data in a Group of Processing Elements to Transpose the Data (docket no. DB001070-000); Method for Manipulating the Data in a Group of Processing Elements to Transpose the Data Using a Memory Stack (docket no. DB001069-000); and Method of Rotating Data in a Plurality of Processing Elements (docket no. DB001063-000), all filed concurrently herewith.

BACKGROUND OF INVENTION

[0002] The present invention relates generally to parallel processing and, more specifically, to parallel processing in an active memory device or single instruction, multiple data (SIMD) computer.

[0003] A single, synchronous dynamic random access memory (SDRAM) chip has an internal data bandwidth of greater than 200 G bits/s and a very wide data bus (thousands of bits). That vast data bandwidth provides an opportunity for high performance. Active memories represent one effort to use that vast data bandwidth to improve performance.

[0004] An active memory is a memory device which has a built in processing resource. One of the principal advantages of active memory is that data is processed close to where it is stored. Usually the processing resource is a highly parallel computer system which has processing power to exploit the very high data bandwidths available inside a memory system. An example of an active memory system is illustrated in Figure 1.

[0005] In FIG. 1, a main memory 10 appears as a traditional memory to a CPU 12 except that the main memory 10, by virtue of memory processors 14, can be instructed to perform tasks on its data without the data being transferred to the CPU 12 or to any other part of the system over a system bus 16. The memory processors 14 are a processing resource distributed throughout the main memory 10. The processing resource is most often partitioned into many similar processing elements (PEs). The PEs are usually simple and operate in parallel. In such a system,

the work of the CPU 12 is reduced to various operating system tasks such as scheduling. A substantial portion of the data processing is performed within the main memory 10 by virtue of the memory processors 14.

[0006] Active memory systems have a long history. The earliest systems were built in the 1960's. However, until the advent of integrated logic and current DRAM technologies, active memory computers were always expensive, special machines, excluded from mass market applications. For active memory to be effective, the organization of data in the PE array is an important consideration. Hence, the provision of an efficient mechanism for moving data from one PE to another is an important consideration in the design of the PE array.

[0007] In the past, several different methods of connecting PEs have been used in a variety of geometric arrangements including hypercubes, butterfly networks, one-dimensional strings/rings and two-dimensional meshes. In a two-dimensional mesh or arrays, the PEs are arranged in rows and columns, with each PE being connected to its four neighboring PEs in the rows above and below and columns to either side which are sometimes referred to as north, south, east and west connections.

[0008] Disclosed in G.B. Patent Application Serial No. GB02215 630, entitled Control of Processing Elements in Parallel Processors, filed September 17, 2002 is an arrangement in which a column select line and a row select line can be used to identify processing elements which are active, e.g. capable of transmitting or receiving data. The ability to use a row select signal and a column select signal to identify active PEs provides a substantial advantage over the art in that it enables data to be moved through the array of PEs in a nonuniform manner. However, the need still exists for enabling PEs within the array to work independently of its neighboring PEs even though each PE within the array has received the same instruction.

SUMMARY OF THE INVENTION

[0009] The present invention is directed to a method for generating the reflection of data in a plurality of processing elements comprising shifting the data along, for example, each row in the plurality of processing elements until each processing element in the row has received all the data held by every other processing element in that row. Each processing element stores and outputs final data as a function of its position in the row. A similar reflection along a horizontal line can be achieved by shifting data along columns instead of rows. The most general

configuration for a plurality of processing elements, where a reflection makes geometric sense, would be an N-dimensional prism, e.g. an (N-1) dimensional collection of M processing elements that is extended into the remaining Nth dimension; that is, by repeating each of the M processing elements L times along the height of the 'column' (or row). Examples of 3-D prisms include a triangular prism, a rectangular prism (cuboid or box), and a circular prism (cylinder). More complex prisms with irregular (but constant) cross-sections, can also be reflected. Prism networks in higher dimensions are also possible but have no everyday equivalent. The two faces at the ends of the prism have to be 'wrap' connected (as discussed below) for the purposes of the reflection algorithm described below.

[0010] The present invention is also directed to a method for generating the reflection of data in an array of processing elements comprising shifting the data along either the rows or the columns in the array a number of times equal to N-1 where N equals the number of processing elements in the rows or columns, respectively. Data is output from each processing element as a function of that element's position in either the row and column.

[0011] The present invention is also directed to a method for reflecting data in a matrix of processing elements about a vertical line comprising shifting data between processing elements arranged in rows. An initial count is set in each processing element according to the expression $(2 \times \text{Col_Index}) \times \text{Mod}(\text{array size})$. In one embodiment, a counter counts down from the initial count in each active processing element as a function of the number of shifts that have been performed. Output is selected as a function of the current count. A similar reflection about a horizontal line can be achieved by shifting data between processing elements arranged in columns and setting the initial count according to the expression $(2 \times \text{Row_Index}) \times \text{Mod}(\text{array size})$. The present invention contemplates hardware, e.g., memory containing an ordered set of instructions, for carrying out the disclosed methods. The present invention represents an efficient method for obtaining the reflection of an array of data. Other advantages and benefits will be apparent from the Description of the Invention appearing below.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] For the present invention to be easily understood and readily practiced, the present invention will be described in conjunction with an exemplary embodiment, for purposes of illustration and not limitation, in conjunction with the following figures wherein:

[0013] FIG. 1 is a block diagram illustrating the concept of active memory;

[0014] FIG. 2 is a high level block diagram of one example of an active memory on which the methods of the present invention may be practiced;

[0015] FIG. 3 is a high level block diagram of one example of a PE;

[0016] FIG. 4 is a diagram illustrating one type of logic circuit that may be used to interconnect the PE illustrated in FIG. 3 to other PEs;

[0017] FIG. 5 illustrates one method of interconnecting PEs to form an array of PEs;

[0018] FIGs. 6A and 6B illustrate one example of an edge shift;

[0019] FIGs. 7A and 7B illustrate one example of a planar shift;

[0020] FIGs. 8A and 8B illustrate one example of a wrap shift;

[0021] FIGs. 9A and 9B illustrate one example of a vector shift;

[0022] FIGs. 10A and 10B illustrate another example of a vector shift;

[0023] FIGs. 11A and 11B illustrate one example of a data broadcast from the edge registers in which a row and column select function enabled;

[0024] FIGs. 12A and 12B illustrate one example of a broadcast in which only one column is selected;

[0025] FIGs. 13A and 13B illustrate one example of selected edge registers being loaded with the AND of selected columns;

[0026] FIGs. 14A and 14B illustrate another example of a data broadcast;

[0027] FIGs. 15A and 15B illustrate an initial matrix of data and a reflection of that initial matrix of data, respectively;

[0028] FIG. 16A illustrates the data appearing in the first row of the matrix of FIG. 15A while FIGs. 16B – 16H illustrate the data for seven consecutive wrap shifts from west to east, respectively;

[0029] FIG. 17 illustrates the initial value for the counter within each processing element to effect a reflection of the initial matrix of data; and

[0030] FIGs. 18A – M illustrate the steps carried out on the first row of data to effect the reflection.

DESCRIPTION OF THE INVENTION

[0031] Illustrated in FIG. 2 is a high level block diagram of one example of an active memory device 18 on which the methods of the present invention may be practiced. The reader should understand that the methods of the present invention are generally applicable to any group of processing elements having the necessary physical connections between PEs to enable the manipulation of data as required by the methods. The hardware illustrated in FIG. 2 is disclosed for purposes of illustration and not limitation. Furthermore, those of ordinary skill in the art will recognize that the block diagram of FIG. 2 is an overview of an active memory device with a number of components known in the art being omitted for purposes of clarity.

[0032] The active memory device 18 of FIG. 2 is intended to be deployed in a computer system as a slave device, where a host processor (e.g. CPU 12 in FIG. 1) sends commands to the active memory device 18 to initiate processing within the active memory device 18. A complete processing operation, i.e., data movement and processing, in the active memory device 18 will usually consist of a sequence of many commands from the host to the active memory device 18.

[0033] The active memory device 18 may have two interfaces, a bus interface 20 and a host memory interface 22, for interfacing with the host or other external logic for the purposes of data input, data output and for control. The host memory interface 22 (data input/output ports) of the active memory device 18 is similar in its operation to the interface of a synchronous DRAM. To access data within a DRAM array 24, the host must first activate a page of data. Each page may contain 1024 bytes of data and there may be 16384 pages in all. Once a page has been activated, it can be written and read through the, for example, 32 bit data input/output ports. The data in the DRAM array 24 is updated when the page is deactivated.

[0034] In the active memory device 18 the input and output ports are separate, or they may be combined into a single bi-directional input/output port. A control output may be provided to control a bi-directional buffer servicing the single bi-directional input/output port.

[0035] The host memory interface 22 may operate at twice the frequency of the master input clock. A copy of the 2x clock may be driven off-chip as a timing reference. Unlike a traditional DRAM, the access time for the host memory interface 22 port takes a variable number of cycles to complete an internal operation, such as an activate or deactivate. A ready signal (rdy) is provided to allow the host to detect when the command has been completed.

[0036] The control or command port (cmd) may be a straightforward 32 bit synchronous write/read interface. Writes place both data and the corresponding address into a FIFO 26 of a task dispatch unit 28, which holds the commands until they are executed in the order they were issued. This arrangement allows a burst of commands to be written to the active memory device 18 suiting the burst operation of many peripheral buses. Reads may operate directly.

[0037] The command port is also synchronous, running at the same frequency as the master input clock. Similarly to the host memory interface 22 port, the clock may be driven out as a timing reference.

[0038] In addition to the two address-mapped ports, the active memory device 18 has an interrupt output (intr) which is used to alert its host to various different conditions.

[0039] Internal control in the active memory device 18 is handled by three processors. The task dispatch unit 28 (mentioned above) receives commands from the command port, interprets them and passes them on to the other two processors, a DRAM control unit 30 and an array sequence controller 32. The task dispatch unit 28 also maintains the addresses for operand placement in an array processor register file (RF) and enables access to on-chip resources such as a program memory 34.

[0040] The DRAM control unit 30 controls the DRAM array 24. The DRAM control unit 30 arbitrates between requests for DRAM array 24 access from the host through host memory access registers (H) and through the host memory interface 22. The DRAM control unit 30 also schedules DRAM array 24 refreshes.

[0041] The array sequence controller 32 controls an array or two dimensional mesh of PEs 36. The sequence controller 32 also executes a program from the program memory 34 and broadcasts control signals into the array of PEs 36. The DRAM control unit 30 and array sequence controller 32 may have a synchronization mechanism, whereby they can link the execution of tasks in either processor.

[0042] The active memory device 18 may contain, according to one embodiment, sixteen 64k x128 eDRAM cores. Each eDRAM core is closely connected to an array of sixteen PEs, making 256 (16 x 16) PEs in all.

[0043] FIG. 3 is a high level block diagram of one example of a PE 37. The PE 37 is comprised of a set of Q registers and a shift network 38 which interact with a set of M registers and another shift register 40. One of the sets of registers and shift network 38, 40 receives inputs from

various registers, such as register R0, R1, R2 and 0. The output of the registers and shift networks 38, 40 is input to an arithmetic logic unit (ALU) 42. The ALU 42 is capable of performing various arithmetic functions on its input such as addition, subtraction, etc. as is known. The ALU 42 is in communication with condition logic 44 and a result pipe 46.

[0044] The result pipe 46 is a series of interconnected registers R0, R1, R2 and a neighborhood connection register X, which may be used to output a final value. The result pipe 46 also receives through a multiplexer 47 data in the form of an output signal X from its four neighbors, one to the north (XN), one to the east (XE), one to the south (XS) and one to the west (XW). If the PE 37 happens to be located on an edge of an array, then it may be receiving data from an edge register or a PE in the same row or column, but on an opposite edge, as will be described in greater detail below.

[0045] The result pipe 46 is in communication with a register file (RF) 48 which in turn is in communication with an interface 50. The interface 50 may include a DRAM interface 52 as well as access to the host memory access registers (H).

[0046] The reader should recognize that the PE 37 illustrated in FIG. 3 is exemplary only and is not intended to limit the present invention. For example, the number and location of registers and shift networks may vary, the complexity of the ALU 42 and condition logic 44 may vary, the number of registers and interconnection of registers in the result pipe 46, the size and number of register files, and connection to neighboring PEs as well as other logic may be varied while remaining within the scope of the present invention. The particular architecture illustrated in FIG. 3 was selected to provide a rich register set to enable fairly complex multi-byte operations to be kept within the PE as much as possible.

[0047] For example, the Q registers and shift network 38 allow for data shifting within the 32 bits of the Q register to the left (most significant direction) one, two, four or eight places and eight places to the right as well as for merging data back into a floating point format. The M registers and shift network 40 allow for data shifting within the 32 bits of the M register to the right (least significant direction) one, two, four or eight places and for demerging data from floating point into a signed magnitude plus exponent format. The result from the ALU 42 can be loaded into register R0 while the input from the register file 48 can be loaded into either register R1 or register R2. The neighborhood connection register X can be used as a flexible member of the result pipeline allowing a pipeline length of up to four to be programmed within the PE 37.

The X register can be loaded from the R0, R1 or R2 registers, or from the neighborhood interconnection input (the X register of a neighboring PE). The output of the X register can be fed back into the result pipeline at R1 or R2. The register file 48 may be implemented as a 128 entry by 8 bit register file implemented as a synchronous static RAM.

[0048] The DRAM interface 52 may contain two registers, a RAM IN register and a RAM OUT register. Input from the DRAM 24 of FIG. 2 may be held in the RAM IN register while output to the DRAM 24 is held in the RAM OUT register. The RAM IN and RAM OUT registers may reside in the clock domain of the DRAM 24 which typically uses a slower or divided clock derived from the same source as the clock used for the PE array 36. The RAM IN and RAM OUT registers may be controlled directly from the DRAM control unit 30 and are not visible to the programmer. Data can be transferred into and out of the register file 48 using stolen cycles. Data can also be transferred to/from the host memory access registers (H) without stealing cycles from processing in the PE 37.

[0049] Eight host memory access registers (H) may be provided which allows for a short burst of four or eight bytes to be transferred into or out of the DRAM 24 for host access. Those registers may be multiplexed and be visible from the host memory interface 22 (see FIG. 1) as a page of data. More details about the PEs may be found in G.B. Patent Application No. 0221562-2 entitled Host Memory Interface for a Parallel Processor and filed September 17, 2002, which is hereby incorporated by reference.

[0050] FIG. 4 is a diagram illustrating one type of logic circuit that may be used to interconnect PEs of the type illustrated in FIG. 3. The reader will understand that many types of logic circuits may be used to interconnect PEs depending upon the functions to be performed. Using the logic circuit of FIG. 4 to interconnect PEs may result in an array of PEs 36 of the type illustrated in FIG. 5.

[0051] Turning now to FIG. 5, the X register within the result pipe 46 of each PE is driven out as, for example, an eight bit wide X output. Eight bits has been chosen in connection with this architecture as the data width for the PE-PE interconnect to keep a balance between the data movement performance of the array and the improved computational performance. Other sizes of interconnects may be used. The X output is connected to the neighboring inputs of each PE's closest neighbors in the north and west directions. To the south and east, the X output is combined with the input from the opposite direction and driven out to the neighboring PE.

[0052] At the edges of the array 36, the out-of-array connection is selected through a multiplexer to be either the output from the opposite side of the array or an edge/row register 54 or an edge/col. register 56. The edge registers 54, 56 can be loaded from the array output or from the controller data bus. A data shift in the array can be performed by loading the X register from one of the four neighboring directions. The contents of the X register can be conditionally loaded on the AND gate of the row select and column select signals which intersect at each PE. When the contents of the X register is conditionally loaded, the edge registers 54, 56 are also loaded conditionally depending on the value of the select line which runs in the same direction. Hence, an edge/row register 54 is loaded if the column select for that column is set to 1 and an edge/col register 56 is set if the row select is set to 1. The reader desiring more information about the hardware configuration illustrated in FIG. 5 is directed to G.B. Patent Application GB02215 630, entitled Control of Processing Elements in Parallel Processors filed September 17, 2002, which is hereby incorporated by reference.

[0053] With the hardware previously described, a number of shifting operations may be performed as illustrated in FIGs. 6A, 6B through 10A, 10B. In FIG. 6A and 6B, an edge shift is illustrated. In the edge shift, the edge/col registers 56 are active as the data is shifted left to right (west to east) as shown in FIGs. 6A, 6B. The reader will recognize that an edge shift may be performed in the other direction, right to left (east to west). Alternatively, edge shifts may be performed by using the edge/row registers 54 in a north to south or south to north direction.

[0054] Illustrated in FIGs. 7A, 7B is a planer shift. In the planer shift there is no wrap around from the edge of the array. The reader will recognize that in addition to the planer shift illustrated in FIGs. 7A, 7B, planer shifts from east to west, north to south, and south to north may also be performed.

[0055] Illustrated in FIGs. 8A, 8B is a wrap shift. In the wrap shift, the edge/col registers 56 do not participate. Additionally, wrap shifts from east to west, north to south and south to north may be performed.

[0056] Illustrated in FIGs. 9A, 9B is a vector shift. Again, the edge/col registers 56 do not participate. Furthermore, the output of the PE in the bottom right corner of the array wraps to the input of the PE in the upper left corner of the array. In FIGs. 10A and 10B, a vector shift in the direction opposite to the direction of FIGs. 9A, 9B is illustrated. The reader will recognize that vector shifts from north to south and south to north may also be performed.

[0057] Returning to FIG. 5, the PE-PE interconnect may also provide a broadcast and broadcast network. Connections or buses 58 extend north to south from a column select register 59 and connections or buses 60 extend west to east from a row select register 61. Also provided is row broadcast/broadcast AND chain 62 and a column broadcast/broadcast AND chain. When used for data broadcast or broadcast, these connections (column buses 58 and row buses 60) act as if driven by open drain drivers; the value on any bit is the wire-AND of all the drivers outputs. Three control signals (broadcast, broadcast and intercast) determine the direction of the buses as follows:

- If broadcast is set to 1, any PE for which the corresponding bits of the row select register 61 and column select register 59 are both set will drive both the row buses 60 and the column buses 58. Note that if no PEs in a row or column drive the bus, the edge register at the end of that row or column will be loaded with 0 x FF.
- If broadcast is set to 1, the row bus 60 is driven from the row select register 61 and the column bus 58 is driven from the column select register 59 and any PE for which the corresponding bits of the row select register 61 and column select register 59 are both set will be loaded from one of the row or column inputs, according to which is selected.
- If intercast is set to 1, any PE in which its A register is 1 will drive its output onto its row bus 60 and column bus 58 and any PE for which the corresponding bits of the row select register 61 and column select register 59 are both set will be loaded from one of the row buses 60 or column buses 58, according to which is selected.

[0058] With the aforementioned connections, a number of operations are possible, some of which are illustrated in FIGs. 11A, 11B through 14A, 14B.

[0059] In FIGs. 11A, 11B, data is broadcast from edge/col registers 56 with the column select register 59 and row select register 61 set as illustrated in FIG. 11A. As a result, data is latched in the PEs as shown in FIG. 11B in which four PEs are active, and the remainder of the PEs in the array are inactive.

[0060] In FIGs. 12A, 12B, a broadcast instruction is illustrated in which one column is selected by setting the value for that column's bus 58 to 1. In this broadcast-column operation, only those edge /col. registers 56 for which the row select register 61 bits are set, will be loaded.

Similarly, in a broadcast-row operation (not shown), only those row/edge registers 54 for which the corresponding column select register 59 bits are set, will be loaded.

[0061] FIGs. 13A, 13B illustrate a broad catch instruction. In the illustrated example, the column select register 59 and row select register 61 are used to select the PEs whose values will be AND'ed together and loaded in the corresponding edge/col registers 56. In FIGs. 13A, 13B, the column edge registers 56 are loaded with the AND of selected columns, except where the row select is 0.

[0062] In FIGs. 14A, 14B, an example of an intercast operation is illustrated. In an intercast operation, PEs which drive onto the row buses 60 and column buses 58 are determined by each PE's A register value. The PEs which are loaded are determined by the row and column selects, just like for a broadcast. In FIG. 14A, data is broadcast from the X registers of those PEs where A equals 1 while in FIG. 14B, the column select register 59 and row select register 61 together activate those PEs into which data will be written.

[0063] Using the aforementioned instructions or operations, a group of instructions may be combined into an instruction set for manipulating data within the array 36 of PEs. The instruction set may include a single instruction or operation or a combination of instructions. Each individual instruction is carried out though a series of shifts.

[0064] In operation, an input matrix of data is placed on the shift network, and moved around by using a combination of north, south, east and west shifts. In addition, the column select register 59 and row select register 61 may be used to determine which of the PEs is active. The exact combination of active PEs, instructions, and direction in which the instruction (shift) is performed will depend upon the particular array manipulation required. As the instructions are executed and the shifting proceeds, each PE will be presented with different array values. For example, if a wrap shift is performed a number of times equal to the number of PEs in a row, each PE in the row will see every value held by all of the other PEs in the row.

[0065] A PE can conditionally select any of the values it sees as its final output value by conditionally loading that value, which is representative of an output result matrix. However, only one value, the desired result, is loaded.

[0066] All X values are passed through the PE; the required output value is conditionally loaded once it has arrived in the PE. The conditional loading can be done in various ways. e.g. by using any PE registers except X, R1, or R2. An example is shown below.

Clock Cycle	PE C + 0		PE C + 1		PE C + 2		PE C + 3
T + 0	$X \leftarrow xe(\text{east})$	\Leftarrow	$X \leftarrow xe$	\Leftarrow	$X \leftarrow xe$	\Leftarrow	$X \leftarrow xe$
	\Downarrow		\Downarrow		\Downarrow		\Downarrow
T + 1	$R1 \leftarrow X$		$R1 \leftarrow X$		$R1 \leftarrow X$		$R1 \leftarrow X$
	\Downarrow		\Downarrow		\Downarrow		\Downarrow
T + 2	$\langle \text{cond} \rangle ? R0 \leftarrow R1$		$\langle \text{cond} \rangle ? R0 \leftarrow R1$		$\langle \text{cond} \rangle ? R0 \leftarrow R1$		$\langle \text{cond} \rangle ? R0 \leftarrow R1$

- At time T+0: The X register reads data from the X register on the PE to the East. This shifts data to the left (or West).
- At time T+1: The R1 register unconditionally reads the data off the shift network (X register)
- At time T+2: The R0 register conditionally loads the data from R1. (i.e. if $\langle \text{cond} \rangle = 1$).

[0067] The timing of the loading is achieved by maintaining a current count in a local counter, which is typically implemented in software. In one embodiment, the local counter is set to an initial value. The local counter can be set in a variety of ways, including loading the counter with the initial value or calculating the initial value locally based on the processing element's location in the matrix (or array) and the function being performed on the data. Thereafter, at certain points in the shifting process, the counter is decremented. For example, the counter may be decremented once for each shift that occurs, or may be decremented once per n clock cycles where n clock cycles equals one shift. As stated, the initial value of the counter depends on its position in the matrix or array and is given by the general function $f(\text{Row_Index}, \text{Col_Index})$, where the exact form of $f()$ will depend on the particular array manipulation required. When the counter reaches a non-positive value (i.e., zero or negative) the PE selects the data to be loaded into the output matrix.

[0068] Other ways of achieving the same result include resetting the counter to zero and loading each PE with a target value. Thereafter, the counter is incremented producing a current count. When the current count equals the target value, the data value is selected as the final output value

to be loaded into the output matrix. Generally, a counter is set to a first known value. Then, at certain programmable points in the algorithm, the value of the counter may be altered, up or down, by a programmable amount. Storing occurs when a current count in the counter hits a pre-defined target value. In the description below, instead of using "non-positive values" and conditional latching, the use of a target value of "zero" removes the need for conditional latching.

[0069] FIG. 15A illustrates a matrix of data while FIG. 15B illustrates a reflection of the matrix of data illustrated in FIG. 15A. A matrix of data may be represented by PEs arranged in rows and columns or PEs arranged in rows extending in the x and z directions and in columns. FIG. 16A illustrates the data appearing in the first row of the matrix of FIG. 15A while FIGs. 16B through 16H illustrate the data as it appears as a result of seven consecutive wrap shifts from west to east, respectively. In FIG. 16B, after the first shift, the data "H" and "D" appearing in columns 1 and 5 represents the data in the first row of the reflection of FIG. 15B. Similarly, in FIG. 16D the data "G" and "C" appearing in positions 2 and 6 after the third wrap shift represent the final output data as seen in FIG. 15B. In FIG. 16F the data "F" and "B" appearing in positions 3 and 7 after five shifts is the reflected data while in FIG. 16H the data "E" and "A" appearing in positions 4 and 8 after seven shifts is representative of the reflected data.

[0070] Using the expression $(2 \times \text{Col_Index}) \text{ MOD } (8)$, the local counters in each of the processing elements may be set to an initial count as illustrated in FIG. 17.

[0071] FIGs. 18A through 18M illustrate input data, output data and counter values through the process of shifting data. In FIG. 18A, the input data is initialized and the counters set to their initial values as illustrated. Thereafter, as illustrated in FIG. 18B, there is a first right shift which changes the input data as illustrated in the top row of FIG. 18B. In FIG. 18C, the counter values are tested and it is seen that the counters in positions 1 and 5 are nonpositive. Accordingly, the input data is latched as the final output data with "H" being latched in position 1 and "D" being latched in position 5. Thereafter, in step 4, the first decrement of the counters is performed resulting in the values shown in the third row of FIG. 18D.

[0072] In FIG. 18E, the process is repeated with a second shift to the right resulting in the data as shown in the first row of FIG. 18E. In FIG. 18F, the counters for those positions which have not yet latched data are tested, and it is determined that all of the values are positive such that no data

is latched. Thereafter, in step 18G, each counter is decremented again resulting in the values shown in the third row of FIG. 18G.

[0073] In FIG. 18H, the process is repeated with the third right shift being performed resulting in the data as shown in the first row of FIG. 18H. Thereafter, in FIG. 18I, the value of the counters corresponding to those PEs which have not yet latched data are tested and it is determined that the PEs in positions 2 and 6 have local counters having a current count which is not positive. Accordingly, the data "G" is latched in position 2 while the data "C" is latched in position 6. In step 18J, the counters are once again decremented resulting in the counts as shown in the third row of FIG. 18J.

[0074] The process is continually repeated until step 20, represented in FIG. 18K, which illustrates the seventh right shift. In FIG. 18L, the counters are tested and it is determined that the current count in the processing element in position 4 and the current count in the processing element at position 8 are nonpositive. Accordingly, the data "E" is latched by the processing element in position 4 while the data "A" is latched in the processing element in position 8. In step 22, represented in FIG. 18M, the counters are decremented one last time, although that step is not necessary as it can be seen from FIG. 18L, second row, that all of the data needed for a reflection of the first row has been latched. FIGs. 18A through 18M illustrate one embodiment for maintaining a current count in local counters within each processing element. Those of ordinary skill in the art will recognize that other methods of maintaining a current count, as well as counting up and counting down, testing for values other than nonpositive values, e.g. a target value, can be carried out while remaining within the scope of the present invention.

[0075] By using the method of the present invention, PEs within a group of PEs can be individually controlled as to the output value which the PE selects for output into the final matrix. Thus, although all of the PEs are responding to the same command, e.g., an east to west wrap shift, each of the PEs is capable of selecting different data at different points during the execution of the instruction thereby enabling various types of data manipulations. Furthermore, by determining which PEs are active, additional flexibility is provided so that subsets of data can be manipulated.

[0076] Although the figures illustrate a two-dimensional (2D) array connected as a mesh the present invention is applicable to other configurations. Accordingly, the phrase "plurality of processing elements" is to be broadly construed to include 2D and 3D collections of PEs

connected in any known manner. For example, the PE's could be connected in shapes other than as illustrated in the figures, e.g., a cube. That would have $f(x_Index, y_Index, z_Index)$. An n-dimensional hypercube would have n dimensions and $f(d(0), d(1), d(2) \dots d(n-1))$.

[0077] Additionally, the network need not be connected as a mesh. For example, a simple extension may be implemented by providing two extra connections, one to the PE halfway across the row and the other to the PE halfway down the column. For that example there would be two more shift connections. In addition to the north, east, south, and west shifts, there could also be Half_Row and Half_Col shifts. Both of the above changes could be used at the same time. For example, a four dimensional hyper-cube with half-way connections would have twelve shift options.

[0078] While the present invention has been described in connection with a preferred embodiment thereof, those of ordinary skill in the art will recognize that many modifications and variations such as those previously discussed are possible. The present invention is not to be limited by the foregoing description but only by the following claims.

What is claimed is:

1. A method for generating the reflection of data in a plurality of processing elements, comprising;
shifting the data along either the rows or columns of the plurality of processing elements until the processing elements in the rows or columns have received the data held by every other processing element in that row or column, respectively;
selecting data as a final output based on a processing element's position.
2. The method of claim 1 additionally comprising one of loading an initial count into each processing element and calculating an initial count locally based on the processing element's location, said selecting being responsive to said initial count.
3. The method of claim 2 wherein said plurality of processing elements is arranged in an array and said initial count is given by the expression $(2 \times \text{Col_Index}) \times \text{Mod}(\text{array size})$.
4. The method of claim 2 wherein said plurality of processing elements is arranged in an array and said initial count is given by the expression $(2 \times \text{Row_Index}) \times \text{Mod}(\text{array size})$.
5. The method of claim 2 additionally comprising maintaining a current count in each processing element, said current count being responsive to said initial count and the number of data shifts performed, said selecting being responsive to said current count.
6. The method of claim 5 wherein said maintaining a current count includes altering said initial count at programmable intervals by a programmable amount.
7. The method of claim 5 wherein said initial count is decremented in response to said shifting of data to produce said current count.
8. The method of claim 6 wherein said selecting occurs when said current count is non-positive.
9. The method of claim 1 additionally comprising maintaining a local count including setting a counter to a first known value, and counting up from said first known value based on the number of shifts that have been performed, said selecting occurring when a current count equals a target count.
10. The method of claim 1 wherein said shifting includes a wrap shift.
11. The method of claim 10 wherein said wrap shift includes shifting data west to east and east to west along rows, and includes shifting data north to south and south to north along columns.

12. A method for generating the reflection of data in an array of processing elements, comprising:
- shifting the data along either the rows or columns in the array a number of times equal to $N-1$ where N equals the number of processing elements in the rows and columns, respectively;
 - outputting data from each processing element as a function of that element's position in one of the row and column.
13. The method of claim 12 additionally comprising one of loading an initial count into each processing element and calculating an initial count locally based on the processing element's position in one of the row and column, said outputting being responsive to said initial count.
14. The method of claim 13 wherein said initial count is given by the expression $(2 \times \text{Col_Index}) \times \text{Mod}(\text{array size})$.
15. The method of claim 13 wherein said initial count is given by the expression $(2 \times \text{Row_Index}) \times \text{Mod}(\text{array size})$.
16. The method of claim 12 additionally comprising maintaining a current count in each processing element, said current count being responsive to said initial count and the number of data shifts performed, said outputting being responsive to said current count.
17. The method of claim 16 wherein said maintaining a current count includes altering said initial count at programmable intervals by a programmable amount.
18. The method of claim 16 wherein said initial count is decremented in response to said shifting of data to produce said current count.
19. The method of claim 18 wherein said outputting occurs when said current count is non-positive.
20. The method of claim 12 additionally comprising maintaining a local count including setting a counter to a first known value, and counting up from said first known value based on the number of shifts that have been performed, said outputting occurring when a current count equals a target count.
21. The method of claim 12 wherein said shifting includes a wrap shift.
22. The method of claim 21 wherein said wrap shift includes shifting data west to east and east to west along rows, and includes shifting data north to south and south to north along columns.
23. A method for reflecting data in a matrix of processing elements about a line, comprising:

shifting data between processing elements arranged in one of rows and columns;
setting an initial count in each processing element according to one of the expressions

$(2 \times \text{Col_Index}) \times \text{Mod}(\text{array size})$ or

$(2 \times \text{Row_Index}) \times \text{Mod}(\text{array size})$;

modifying said initial count by a programmable amount at programmable intervals to
produce a current count; and

selecting output data as a function of said current count.

24. The method of claim 23 wherein said modifying includes counting down from said
current count.

25. The method of claim 24 wherein said selecting occurs when said current count is a non-
positive value.

26. The method of claim 23 wherein said shifting includes a wrap shift.

27. The method of claim 25 wherein said wrap shift includes shifting data one of east to west,
west to east, north to south and south to north.

28. A memory device carrying a set of instructions which, when executed, perform a method
comprising:

shifting the data along either the rows or columns of the plurality of processing elements
until the processing elements in the rows or columns have received all the data held by every
other processing element in that row or column, respectively;

selecting data as a final output based on a processing element's position.

ABSTRACT

A method for generating the reflection of data in a plurality of processing elements comprises shifting the data along, for example, each row in the array until each processing element in the row has received all the data held by every other processing element in that row. Each processing element stores and outputs final data as a function of its position in the row. A similar reflection along a horizontal line can be achieved by shifting data along columns instead of rows. Also disclosed is a method for reflecting data in a matrix of processing elements about a vertical line comprising shifting data between processing elements arranged in rows. An initial count is set in each processing element according to the expression $(2 \times \text{Col_Index}) \times \text{Mod}(\text{array size})$. In one embodiment, a counter counts down from the initial count in each processing element as a function of the number of shifts that have been performed. Output is selected as a function of the current count. A similar reflection about a horizontal line can be achieved by shifting data between processing elements arranged in columns and setting the initial count according to the expression $(2 \times \text{Row_Index}) \times \text{Mod}(\text{array size})$. The present invention represents an efficient method for obtaining the reflection of data..

FIG. 1


















FIG. 2









Data is broadcast from edge registers




FIG. 11A




FIG. 11B




FIG. 12A








FIG. 12B



[illegible]

FIG. 15A

[illegible]

FIG. 15B

FIG. 16 A

1	2	3	4	5	6	7	8
A	B	C	D	E	F	G	H

Original data

FIG. 16 B

H	A	B	C	D	E	F	G
---	---	---	---	---	---	---	---

1st shift

FIG. 16 C

G	H	A	B	C	D	E	F
---	---	---	---	---	---	---	---

2nd shift

FIG. 16 D

F	G	H	A	B	C	D	E
---	---	---	---	---	---	---	---

3rd shift

FIG. 16 E

E	F	G	H	A	B	C	D
---	---	---	---	---	---	---	---

4th shift

FIG. 16 F

D	E	F	G	H	A	B	C
---	---	---	---	---	---	---	---

5th shift

FIG. 16 G

C	D	E	F	G	H	A	B
---	---	---	---	---	---	---	---

6th shift

FIG. 16 H

B	C	D	E	F	G	H	A
---	---	---	---	---	---	---	---

7th shift

FIG. 17

[illegible]



FIG. 18

Step 1 Initialize

A	B	C	D	E	F	G	H
C	2	4	6	0	2	4	6

A

Step 2 - 1st shift right

H	A	B	C	D	E	F	G
C	2	4	6	0	2	4	6

B

Step 3 - Test (load H & D)

H	A	B	C	D	E	F	G
H				D			
C	2	4	6	0	2	4	6

C

Step 4 - 1st Decrement

H	A	B	C	D	E	F	G
H				D			
-1	1	3	5	-1	1	3	5

D

Step 5 - 2nd shift right

G	H	A	B	C	D	E	F
H				D			
-1	1	3	5	-1	1	3	5

E

Step 6 - Test (Nothing to load)

G	H	A	B	C	D	E	F
H				D			
-1	1	3	5	-1	1	3	5

F

Step 7 - 2nd Decrement

G	H	A	B	C	D	E	F
H				D			
-2	0	2	4	-2	0	2	4

G

Step 8 - 3rd Right Shift

F	G	H	A	B	C	D	E
H				D			
-2	0	2	4	-2	0	2	4

H

Step 9 - 3rd Test (load G & C)

F	G	H	A	B	C	D	E
H	G			D	C		
-2	0	2	4	-2	0	2	4

I

Step 10 - 3rd Decrement

F	G	H	A	B	C	D	E
H	G			0	C		
-3	-1	1	3	-3	-1	1	3

J

Step 20 - 7th Right Shift

B	C	D	E	F	G	H	A
H	G	F		D	C	B	
-6	-4	-2	0	-6	-4	-2	0

K

Step 21 - 7th Test (load E & A)

B	C	D	E	F	G	H	A
H	G	F	E	D	C	B	A
-6	-4	-2	0	-6	-4	-2	0

L

Step 22 - last decrement

B	C	D	E	F	G	H	A
H	G	F	E	D	C	B	A
-7	-5	-3	-1	-7	-5	-3	-1

M

